

2M GENERATING SET – SAWAFUJI ELEMEX SHX 1000



ELEMEX SHX 1000

- ▶ "Super Silent" range
- ▶ Gasoline
- ▶ Super silent
- ▶ INVERTER : High current quality & stability
- ▶ Recoil starter
- ▶ 1,0 KVA max. 1~ 230 V / 50Hz

POWERED by
HONDA™

SERIAL EQUIPMENT :



GASOLINE ENGINE



AIR COOLING




RECOIL STARTER



OIL ALERT WITH
ENGINE SHUT DOWN



1 SCHUKO SOCKET
230V-10/16 AMP.



BATTERY CHARGER
12V DC



SYNCHRONOUS
ALTERNATOR



THERMAL SHUT OFF



VOLTAGE REGULATION:
INVERTER

ENGINE :

Max. power :
Tank capacity :
Autonomy :

HONDA GXH 50

2,5 hp / 1,8 kW
3,7 L
8 h (75% load)

ALTERNATOR :

Max. power :
Nom. power PRP :

SAWAFUJI - INVERTER

1,0 KVA 1~ 230 V

0,9 KW 1~ 230 V

0,68 KW **eco** 1~ 230 V

4 / 3 A 1~ 230 V

Intensity :
Direct current(DC)
Safety class :

8,3 A – 12V

IP23

Noise level :

89 dB(A) LWA / **64 dB(A)** 7 m

Dimensions :

470 x 270 x 380 mm

Weight :

14,0 Kg

OPTIONAL ACCESSORIES :